

# Sandown Wireless

[www.criticalbattery.com](http://www.criticalbattery.com)

<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>CM4486LIPIC</b>

COMPATIBLE RADIOS	Motorola APX 6000, APX 6000XE, APX 7000, APX 7000XE, APX 8000, APX8000XE
REPLACES OEM BATTERY	PMNN4486
COMPATIBLE CHARGERS	Endura EC1-MT19, EC1M-MT19, TWC2M-MT19-D, EC6M-MT19, TWC12M-MT19-D / Logic LEVCA-MT19 / Motorola adaptive IMPRES chargers NNTN7065, NNTN7073, NNTN7080, NNTN7586, NNTN7624 Works in all current IMPRES / IMPRES-2 OEM Chargers
VOLTAGE	7.4V
CAPACITY	3400 mAh, 25.16 Wh
CHEMISTRY / CELL TYPE	LiPo / Kanyo or equivalent
BATTERY TYPE	Smart IMPRES / IMPRES-2 Compatable
OPERATING TEMPERATURE	-10° C to +50° C (discharge) / 0° C to +45° C (charge)
CHARGE CYCLES	500
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes
THERMAL PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	24 Months
PRODUCT PHOTO	 <p>Dimensions (HxWxD): 3.41" x 2.36" x 1.66"</p>

**Sales: Dave Patterson -- Office: 517-281-8829**

**E-mail: [cdpattco@me.com](mailto:cdpattco@me.com) -- Web: [www.criticalbattery.com](http://www.criticalbattery.com)**